




PZT5551

NPN Transistor

Features

Marking: ZT5551

Equivalent circuit



Maximum Ratings (Ta=25 unless otherwise noted)

Item	Symbol	Unit	Conditions	Value
Minimum Collector-Emitter Voltage	V_{CE0}	V	$I_C=1mA, I_B=0$	160
M	EBO	V	$I_E=10uA, I_C=0$	6
Collector Current	I_{2u2E}			

PZT5551

Electrical Characteristics (Ta=25 unless otherwise noted)

Item	Symbol	Unit	Conditions	Min	Max
Collector-Emitter Voltage	V_{CE0}	V	$I_C=1mA_{dc}, I_B=0$	160	-
Collector-Base Voltage	V_{CB0}	V	$I_C=100\mu A_{dc}, I_E=0$	180	-
Emitter-Base Voltage	V_{EB0}	V	$I_E=10\mu A_{dc}, I_C=0$	6.0	-
Collector-base Cut-off Current	I_{CBO}	nA	$V_{CB}=120V_{dc}$	-	50
Emitter-base Cut-off Current	I_{EB0}	nA	$V_{EB}=4.0V_{dc}$	-	50
DC Current Gain	h_{FE}		$I_C=1.0mA, V_{CE}=5.0V_{dc}$	80	-
			$I_C=10mA, V_{CE}=5.0V_{dc}$	80	250
			$I_C=50mA, V_{CE}=5.0V_{dc}$	30	-
Collector-Emitter Saturation Voltage	$V_{CE(sat)1}$	V	$I_C=10mA, I_B=1.0mA$	-	0.15
	$V_{CE(sat)2}$	V	$I_C=50mA, I_B=5.0mA$	-	0.2
Base-Emitter Saturation Voltage	$V_{BE(sat)1}$	V	$I_C=10mA, I_B=1.0mA$	-	1
	$V_{BE(sat)2}$	V	$I_C=50mA, I_B=5.0mA$	-	1
Output Capacitance	C_{ob}	pF	$V_{CB}=10V_{dc}, \dot{I}_E=0, \dot{f}=1MHz$	-	6
Transition frequency	f_T	MHz	$I_C=10mA_{dc}, V_{CE}=5.0V_{dc}, f=30MHz$	100	300

Ordering Information (Example)


PREFERRED P/N	PACKING CODE	UNIT WEIGHT(g)	MINIMUM PACKAGE(pcs)	INNER BOX QUANTITY(pcs)	OUTER CARTON QUANTITY(pcs)	DELIVERY MODE
PZT5551	F2	Approximate 0.11	2500	5000	25000	13" reel

Characteristics (Typical)




PZT5551


Collector-Emitter Saturation Voltage




Base-Emitter Saturation Voltage




Base-Emitter On Voltage



C_{ob}/C_{ib} vs V_{ce}/V_{be}




Power Derating Curve






SOT-223 Package Outline Dimensions



DIMENSIONS				
DIM	INCHES		MM	
	MIN	MAX	MIN	MAX
A	0.0591	0.0670	1.5000	1.7000
D	0.0500	0.0010	0.0010	0.0010
E	0.0000	0.0010	0.0010	0.0010
E1	0.0000	0.0010	0.0010	0.0010
b	0.0000	0.0010	0.0010	0.0010
b1	0.0000	0.0010	0.0010	0.0010
e	0.0000	0.0010	0.0010	0.0010
L	0.0000	0.0010	0.0010	0.0010
⌀	0.0000	0.0010	0.0010	0.0010

SOT-223 Suggested Pad Layout





Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website [http:// www.21yangjie.com](http://www.21yangjie.com) , or consult your nearest Yangjie's sales office for further assistance.