



YJF06C80H1

## N-Channel Enhancement Mode Field Effect Transistor

### Product Summary

$V_{DS}$	800V
$I_D$	
$R_{DS(ON)}$ ( at $V_{GS}=10V$ )	1.2
100% EAS Tested	
100% $V_{DS}$	



## Electrical Characteristics ( $T_J=25$ unless otherwise noted)

Parameter
-----------



# YJF06C80HJ

## Typical Electrical and Thermal Characteristics Diagrams




Figure 1. Output Characteristics





Figure 2.





# YJF06C80HJ




Figure 7. RDS(on) VS Drain Current




Figure 8. Forward characteristics of reverse diode




Figure 9. Normalized breakdown voltage




Figure 10. Normalized Threshold voltage




Figure 11. Current dissipation




Figure 12. Power dissipation




Figure 13. Maximum Transient Thermal Impedance




Figure 14. Safe Operation Area

## Test Circuits & Waveforms




Figure A. Unclamped Inductive Switching (UIS) Test Circuit & Waveform







## YJF06C80HJ

---

### Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website <http://www.21yangjie.com> , or consult your nearest Yangjie's sales office for further assistance.